

Protection against loose connectors

Digital services are seriously impacted by loose connectors:

Pixelation and tiling of video • Reduced data speeds • Poor VoIP voice quality

SignalTight™ Drop Connectors minimize the number of self-installs that become truck rolls

Achieves signal transmission approaching that of a fully-tightened connector, even if left loose

- Unique 7/16" nut profile allows hand tightening while discouraging wrench-tightening on CPEs
- Maintains ground continuity even when very loose
- Reduces QAM errors/packet loss
- Prevents service issues from loose connections
- Ideal for customer self-install kits



Product Specifications

Bandwidth	0 MHz to 3 GHz
Impedance	75 Ohms (nominal)
Return Loss	Minimum -30 dB to 3 GHz
Insertion Loss	Less than .10 dB to 3 GHz
Operating Voltage	90 V (at 60 Hz continuous AC)
Operating Temperature	-40° F to + 140° F (-40° C to 60° C)
Cable Retention (Trishield)	70 lbs (31.75 kg) minimum

Meets or Exceeds all SCTE Specifications

Part Number

EX6XLPLUS	SignalTight™, XL series, 6 series
EX59XLPLUS	SignalTight™, XL series, 59 series

CoreTel s.r.o.
K Cintorínu 64
010 04 Žilina
Slovenská republika

IČO: 47 744 731
IČ DPH: SK202407726

Fio banka a.s. č.ú.:
EUR: 2500577171/8330
CZK: 2100577172/2010
USD: 2400577174/8330

Tel. č.: +421 948 87 55 87
Tel. č.: +421 948 86 55 86
Email: coretel@coretel.eu
Web: www.coretel.eu